

Including HA modules into the CA5500 In Touch network

Excluding a module from the network:

Start with the HA module in the off position.

Press the *exclude* button on the CA5500 (red LED will light)

Press the *on/off* button on the HA module.

(red LED on 5500 should turn blue if successful)

Including a module into the network:

Start from the OFF position on the HA module.

Press the *include* button on the CA5500. The LED should stay a solid blue.

Press the *ON/OFF* button on the HA module. If successful, the CA5500 LED will flash blue, go solid blue, then flash blue again and go out when complete (this could take up to 60 seconds to complete). You MUST wait for this sequence to complete for it to be successfully included into the network. If you get any other indication, or the LED lights up red, the inclusion was not successful. It is recommended that you start over and exclude the module from the network.

Assigning an HA module to a scene:

Start with the HA module in the OFF position.

Press and hold the scene selection number for 10+ seconds until the LED flashes blue.

Once it flashes, turn the HA module ON. The CA network will turn the HA module back to the OFF state. Once it has done that, turn the HA module to the desired state (usually on).

After all modules have been included to this scene (in the same manner), press and hold the scene selection number until the led lights solid blue for a few seconds, then flashes blue twice. That scene is now programmed.